

LOCATION	CONTENTS & FIELD SIZE		REMARKS			
0	Master Code (4 digits)		0670600 *5 5			
4	User 1 code (4 digits)	A	☐	☐	☐	0
8	User 2 code (4 digits)	A	☒	☐	☐	1
12	User 3 code (4 digits)	A	☐	☒	☐	2
16	User 4 code (4 digits)	A	☒	☒	☐	3
20	User 5 code (4 digits)	B	☐	☐	☒	4
24	User 6 code (4 digits)	B	☒	☐	☒	5
28	User 7 code (4 digits)	Arm both areas	☐	☒	☒	6
32	User 8 code (4 digits)	Disarm both areas	☒	☒	☒	7
36	Alarm reset time	(Minutes X 2)	☐	☐	☐	8
38	Entry Time	(Seconds X 10)	☒	☐	☐	9
39	Zone 1 Description	0	☐	☒	☐	10
	Burglary	0	☒	☒	☐	11
	Burglary + Nite arm	1	☐	☐	☒	12
	Burglary + Chime	2	☒	☐	☒	13
	Burglary + Chime + Nite arm	3	☐	☒	☒	14
	Burglary + Entry	4	☒	☒	☒	15
	Burglary + Entry + Nite arm	5				
	Burglary + Entry + Chime	6				
	Burglary + Entry + Chime + Nite arm	7				
	24 Hour main alarm relay					
	24 Hour Secondary Alarm					
40	Zone 2 Description	0				
41	Zone 2 Description	0				
42	Zone 3 Description	0				
43	Zone 4 Description	0				
44	Zone 5 Description	0				
45	Zone 7 Description	0				
46	Zone 8 Description	0				
47	2-Key panic + siren chirp	Off				
	1 = Main Alarm relay, Siren chirp off					
	2 = Secondary Alarm, siren chirp off					
	4 = 2 key panic off, siren chirp on					
	5 = main alarm relay siren chirp on					
	6 = secondary alarm, siren chirp on					
48	Programmable Output 1	0				
	Area A Armed	0				
	Area B Armed	1				
	Beeper Area A	2				
	Beeper Area B	3				
	Secondary Alarm	4				
	Away alarms only	5				
	Courtesy light	6				
	Area B Alarm output	7				
	Strobe	8				
	Garage door 1	9				
49	Programmable output 2		As per 48			
50	Selectable functions					
	None					
	Single key arming	1				
	Sequential entry	2				
	Single key entry + sequential entry	3				
	Partitioning	4				
	Partitioning + single key arming	5				
	Partitioning + sequential entry	6				

L
Y
N
X
P
R
O
G
R
A
M
M
I
N
G

