

24HR ZONES (P23E)

Zones assigned a 24Hr status will cause an alarm whether the panel is in set, unset or monitor mode. This assignment is used on zones monitoring devices such as panic buttons, smoke detectors or plant alarms etc.
NOTE: 24Hr zones can also be Two Trigger.

MONITOR MODE ZONES (P24E)

Monitor Mode or part set is primarily used to provide partial protection to high risk zones when a residence is occupied. Monitor mode allows a user to arm only those zones required as defined at P24E. Zones not included in P24E are automatically excluded when monitor mode is selected.

DAY ZONES (P25E)

DAY ZONES operate only when the panel is totally disarmed i.e. unset with no monitor mode on. A Day Zone is also a normal full set zone becoming active when the panel is armed. DAY ZONES would normally be used with the Momentary Output Timer. DAY ZONES are normally used for door chimes etc.

SIREN LOCKOUT ZONES (P26E)

If selected as Lockout (LED on = Lockout selected) the zone can trigger its assigned alarm output only once during an armed period. If not selected as Lockout, the zone can retrigger the alarm output after the expiry of the Alarm Reset Time.

***NOTE:** Lockout and Two Trigger status cannot be assigned to the same zone, only one of these options is allowed at a time.*

MISCELLANEOUS OPTIONS (P27E)

The following options are available at this address

- 1 Entry Beeps
- 2 Exit Beeps
- 3 Keyswitch Arm/Monitor
- 4 LED Timeout
- 5 Exit Delay X 10
- 6 Auto Exclude
- 7 Disable Single Button Disarm
- 8 Disable Single Button Monitor toggle on keypad port #1